

WAVEGUIDE DIRECTIONAL FILTER

[01] This is a continuation of Application No. 09/857,104, which was a national stage entry of PCT/AU99/01071, and having a 35 U.S.C. 371 acceptance date of September 18, 2001, the disclosure of which is incorporated herein by reference.

Field of the Invention

[02] This invention relates to the technology of combining multiple UHF TV broadcasting transmitters on to a common antenna.

Background of Invention

[03] In this technology it is known to provide a UHF filter/combiner system comprising an assembly of dual bandpass filters whose inputs and outputs are coupled by waveguide hybrid couplers. A disadvantage of this known system is its relatively large size. Another disadvantage of this system is that the dual bandpass filters must be electrically identical, which is difficult to accomplish due to their complexity.

[04] It is also known to provide a UHF filter/combiner that comprises a cascade of dual mode resonant cavities with input and output coaxial coupling elements, such as the "ROTAMODE" device. However, a disadvantage of this form of construction is that the power handling capability of the coaxial input and output elements is limited.

[05] It is also known to use a waveguide directional filter technique at microwave multi-point distribution system (MMDS) frequencies above 2 GHz. Each TV channel at MMDS frequencies occupies a fractional bandwidth of much less than 1%. However, at UHF broadcasting frequencies in the range 470-860 MHz, the fractional bandwidth of a TV channel is of the order of 1% or more, and a conventional waveguide directional filter does not provide a satisfactory electrical performance.

Summary of the Invention

[06] It is an object of the present invention to provide a waveguide directional filter arrangement which can be used at UHF broadcasting frequencies, and avoids the disadvantages of the aforementioned prior art.

[07] According to a first aspect of the invention there is provided a waveguide directional filter arrangement comprising an input waveguide, an output waveguide and an interconnected cascade assembly of two or more cavity resonators, wherein said input waveguide and said output waveguide each include broad wall sections joined by narrow wall sections whose aspect ratio is greater than 2:1.

[08] According to a second aspect of the invention there is provided such a waveguide directional filter arrangement wherein each said waveguide is coupled via an aperture to an end cavity resonator of said cascade assembly, wherein edges of each aperture include inwardly extending curved protrusions of approximately hemicycle-shaped form.

[09] According to a third aspect of the invention there is provided a waveguide directional filter arrangement comprising an input waveguide, an output waveguide and an interconnected cascade assembly of at least three stacked resonator elements, wherein said input waveguide and said output waveguide each include broad wall sections joined by narrow wall sections whose aspect ratio is greater than 2:1, each said waveguide coupled via an aperture to an end resonator of the cascade assembly, wherein at least one pair of non-adjacent cavity resonators are coupled by at least one additional coupling element incorporating an external transmission line.

Brief Description of the Drawings:

[10] The invention will be more clearly understood from the following detailed description in conjunction with the accompanying drawings, in which:

- [11] Figure 1 shows a waveguide directional filter assembly of the present invention;
- [12] Figure 2 shows a more detailed view of the aperture arrangement of the assembly shown in Figure 1;
- [13] Figure 3 shows an alternative aperture arrangement; and
- [14] Figure 4 shows a waveguide direction filter assembly with additional coupling between non-adjacent resonators.

Detailed Description of the Invention

- [15] Referring to Figure 1, the assembly comprises an input waveguide 1 having a narrow band input port and an absorbing termination port; and an output waveguide 2 having a wideband input port and an output port. The waveguides are rectangular having broad walls 3 joined to narrow walls 4 whose aspect ratio is approximately 4:1.
- [16] Waveguides 1 and 2 are connected by six circularly cylindrical aperture coupled cavity resonators 5. Direct coupling between adjacent cavity resonators is provided by circular apertures 6.
- [17] Each end cavity resonator is operatively coupled to its associated rectangular waveguide by a characteristically shaped aperture 7, 7a. Referring to Figure 2, aperture 7a, which is similar to aperture 7 in input waveguide 1, is in the form of a rectangle whose four sides have integral inwardly extending curved protrusions 8, 9, 10 and 11 of hemicycle shape. These hemicycle protrusions significantly influence the electromagnetic coupling from the waveguide into the adjacent cavity resonator.
- [18] It will be understood that the inwardly extending hemicycle protrusions can be in the form of discrete elements, such as for example discs, that can be attached around the edges of a basic rectangular aperture. The position of such discrete elements can be made adjustable to vary the coupling through the aperture.

- [19] Alternatively, the inwardly extending hemicycle protrusions can be in the form of cylinders 12, 13, 14 and 15 as shown in Figure 3. As with the above mentioned discs, the positions of the cylinders can be adjustable to vary the coupling through the aperture. Moreover, a cylindrical form of significant height reduces the electromagnetic coupling of undesirable cavity resonator modes.
- [20] Referring to Figure 4, non-adjacent cavity resonators 16 and 17 of the waveguide directional filter assembly are provided with two additional coupling elements 19 and 20. Each additional coupling element comprises two probes 21 and 22 connected by a transmission line 23. The probes extend into the resonators and are disposed at 90° to one another.
- [21] The power handling capability of the waveguide directional filter arrangement described above can be enhanced by the addition of cooling fins (not shown) on one or more of the cavity resonators.
- [22] Also, tuning elements (not shown) can be added to the cavity resonators.
- [23] In operation, a narrow band signal is injected into the input port of input waveguide 1. This signal is coupled through aperture 7 into the first cavity resonator and launches a circularly polarised wave therein which is coupled through successive circularly cylindrical resonators 5 by means of circular apertures 6 to the output waveguide 2 via aperture 7a, where it produces a directional wave. This signal is added to any existing signals travelling through the same waveguide at other frequencies.
- [24] An absorbing termination coupled to waveguide 1 absorbs any power not coupled into the first resonator.
- [25] An advantage of the waveguide directional filter assembly of the present invention vis-a-vis the prior art assembly using separate hybrids and filters is that the assembly of the present invention is relatively unaffected by temperature differentials which can occur

between separate filters in a hybrid coupled configuration. Such temperature differentials lead to a degradation of performance.